

[Labgear](http://www.labgear.co.uk)<http://www.labgear.co.uk/product-categories/amplifiers/ir-bypass-amplifiers/8-way-home-distribution-unit/>

Export date: Wed Jan 30 9:38:44 2019 / +0000 GMT



8-way Home Distribution Unit



Product Categories: [IR Bypass Amplifiers and Accessories](#)

Product Page: <http://www.labgear.co.uk/product-categories/amplifiers/ir-bypass-amplifiers/8-way-home-distribution-unit/>

Product Summary

Specifications

Number of inputs
 Number of outputs
 Gain UHF TV to Downlink
 Noise Figure

Frequency ranges

UHF TV
 CCTV
 FM
 DAB
 LNB1
 LNB2
 UHF TV line power for pre-amp
 UHF TV protection from 4G Class 3
 Gain Uplink to Out
 Return path Out to Uplink
 Return path Gain
 Power on Outs for IR
 LNB line power
 LNB rejection in UHF
 F-connectors
 Power requirements

LDU608R

5 to DownLink + LNB2
 8 from Uplink
 10dB
 Typ. 2.5dB
 470-782MHz
 470-862MHz
 88-108MHz
 217-230MHz
 950-2300MHz
 950-2300MHz
 12V DC 100mA
 Typ, 45dB
 10dB
 5-10MHz
 0dB
 >9V/15mA short circuit protected
 20V 400mA
 >40dB
 >IEC 60169-24
 220-240V~50/60hz 250mA typical

[Click here](#) to view the instruction manual.



Product Description

LDU608R - 6 input 8 output

- Distribute a number of RF signals from range of sources to points all around your home
- Combine in signals from SkyHD or any HDMI source via the EM1000
- Control additional signal source from any of the 8 outputs
- 5 inputs combined and fed to downlink. Uplink fed to 8 outlets with DigiLink bypass



Product Attributes

- Part Number: LDU608R

Product added date: 2016-10-27 10:10:45

Product modified date: 2019-01-29 15:49:02

Export date: Wed Jan 30 9:38:44 2019 / +0000 GMT

Product data have been exported from Labgear [<http://www.labgear.co.uk>]

Product Print by [WooCommerce PDF & Print](#) plugin.